

# 16 CH 720P HD-SDI REAL-TIME DVR

SA-16400SDI-EX (1U)

720P



## Specifications

<b>MODEL</b>	SA-16400SDI-EX (1U)	
<b>System</b>	<b>Compression Format</b>	High Profile H.264
	<b>OS</b>	Embedded Linux
<b>Video</b>	<b>Input</b>	16CH HD-SDI BNC
	<b>Standard Output</b>	VGA
	<b>Advanced Output</b>	HDMI
<b>Audio</b>	<b>Input</b>	1CH
	<b>Output</b>	1CH
	<b>Two way audio</b>	Yes
<b>Recording</b>	<b>Real-Time Recording</b>	16CH 720P HD-SDI Real-Time
	<b>1080P HD-SDI</b>	No
	<b>720P HD-SDI</b>	480FPS (NTSC)/400FPS (PAL)
	<b>960H</b>	No
	<b>D1</b>	No
	<b>CIF</b>	No
	<b>Recording Mode</b>	Schedule, Manual, Motion, Sensor
<b>Playback</b>	<b>Playback Channel</b>	8CH
	<b>Search Mode</b>	Time, Event, File Management
<b>Backup</b>	<b>USB</b>	1 USB 2.0 Port
	<b>DVD Burner</b>	Optional
	<b>Backup Format</b>	AVI/DAT
<b>Remote Application</b>	<b>Dual Stream</b>	Master Stream 1-25/30FPS@720P, Sub-Stream 1-25/30FPS@CIF
	<b>Browser</b>	IE, Chrome, Safari, Firefox (Mac OS, Windows XP/Vista/7/8)
	<b>Master Stream in Network</b>	Yes
	<b>CMS</b>	Yes
	<b>3G</b>	ProvisionCAM for iOS/Android
<b>User Access</b>	10 Users Online with Professional Authority Management	
<b>Alarm</b>	<b>Input</b>	No
	<b>Output</b>	No
<b>Storage</b>	<b>HDD</b>	2 SATA (3TB)
	<b>E-SATA</b>	No
<b>PTZ</b>	<b>Connection</b>	1xRS-485
	<b>Supported Protocol</b>	Pelco D, Pelco P, Samsung, Visca
	<b>Supported Controls</b>	Pan, Tilt, Zoom, Preset, Cruise, Scan, Iris, Focus
<b>Network</b>	<b>Ethernet</b>	1000 Mbps (RJ-45)
	<b>Protocol</b>	TCP/IP, DHCP, DDNS, NTP, SMTP
<b>Others</b>	<b>Dimension</b>	W430xD300xH55mm
	<b>IR Controller</b>	Yes
	<b>Power Supply</b>	DC 12V/4A
	<b>Operating Temperature</b>	0°C ~50°C